

+ Щуп -		Показания мультиметра
Выводы микросхемы UC3842B		
1	2	1900
2	1	1300
1	3	1700
3	1	1500
1	4	∞
4	1	1500
1	5	1900
5	1	640
1	6	∞
6	1	∞
1	7	780
7	1	∞
1	8	900
8	1	1200
2	3	1300
3	2	1600
2	4	1200
4	2	1600
2	5	1200
5	2	660
2	6	1400
6	2	∞
2	7	1300
7	2	∞
2	8	740
8	2	1300
3	4	1400
4	3	1300
3	5	1300
5	3	660
3	6	1500
6	3	∞
3	7	1200
7	3	∞
3	8	680
8	3	1300
4	5	1200
5	4	615
4	6	1500
6	4	∞
4	7	1300
7	4	∞
4	8	720
8	4	1200
5	6	600
6	5	∞
5	7	580
7	5	∞
5	8	550
8	5	1000
6	7	700
7	6	1300
6	8	∞
8	6	1200
7	8	∞
8	7	655